



Follow tutorial to create new passcode, record name, and record greeting.  
Default passcode is 1111

# Mitel's NuPoint Messenger Flow

**Accessing Voice Mail**

**From Your Phone:**  
Press the Message key  
Passcode: \_\_\_\_\_

**From any other Phone:**  
Press the Message  
  
Enter: \* plus your own Mailbox Number followed by another \*  
Passcode: \_\_\_\_\_

**From Outside**  
Dial Auto Attendant number  
*At the start of the Co. greeting . . .*  
• Press \* wait for message center  
• Enter your mailbox number  
• Press \*  
• followed by your Passcode

**IF YOU HAVE A DID NUMBER:**  
Dial your own DID,  
*At the start of your greeting....*  
Press \* (tells system owner is calling)  
Enter your Passcode: \_\_\_\_\_

**Play Messages (7)**

- 7** to Play
- \* Rewind in 5 second increments
  - # Fast Forward in 5 second increments
  - 1 Pause in 30 second increments
  - 8 To skip to Top of next message

- 7 to Play again
- 2 to Answer
- 4 to Give to another user
- 5 to Keep
- 3 to Discard
- 6 to Make a new message
- 9 to eXit message review

*Enter destination mailbox, & record introduction ...*

- 7 to Review
- 3 to Discard and Re-Record
- 2 to Append
- 6 for Message Addressing Options
- 9 to Send and Exit

**Make Message (6)**

- 6** to Make (record) Msg
- Enter Mailbox Number(s),
  - # when finished entering mailboxes
  - # When finished recording message.

- 7 to Review
- 3 to Discard and Re-Record
- 2 to Append
- 6 for Message Addressing Options
- 9 to Send and eXit to Main Menu

**Message Addressing Options:**

- 2 to make Confidential
- 7 to Request Receipt
- 8 to mark Urgent
- 3 to mark for Future delivery

Press 9 to eXit and return to previous menu options.

**User Options (8)**

- 8** for User Options

- 4 to change Greeting
- 6 to change Name
- 7 to change Passcode
- 5 for Distribution Lists (01 - 09)
- 2 to change Call Schedule Options
- 8 to repeat Tutorial (reset mbx passcode, greeting, and passcode)
- 9 to eXit to Main Menu
- 5 to Listen to Greeting/Name
- 7 to Record Greeting/Name
- 4 to change your Extended Absence Greeting
- 9 to eXit to Previous Menu

**9** to Exit

**0** for an Operator

## Initializing Your Voice Mailbox



**Access your voice mailbox by pressing the Message key**

**The Voice Mail system will now guide you through the steps to set up your mailbox.**

**Your default password is 1111**

**You will need to press 8 (User options) to do the following:**

**Press 7 To create a new Passcode (4 to 10 digits)**

**Press 4 To record your mailbox Greeting**

**Press 6 To record your Name**

### **Suggested Greeting:**

**Hello, you have reached the voice mailbox for \_\_\_\_\_ I'm sorry that I'm not available to take your call at this moment. Please leave your contact information and the reason for your call, and I will respond as soon as possible. Thank you.**

**{Remember to press the # key to tell the system when you are done recording.}**

**You may change your passcode, greeting, or name simply by going back into the 8 User options.**

**Your telephone is programmed to forward to the Voice Mail system upon a busy or no answer condition without any need for you to activate anything. A message light on your telephone will let you know when a message has been left for you in your mailbox.**